

MEGMEET

Function code	Name	Description	Default value	Change
		5.5 kW and below: 10 s 5.5 to 30 kW (included): 20 s Above 30 kW: 40 s		
P02.14	Deceleration time 1	0.0 to 6000.0 s	Model dependent	<input type="radio"/>
P02.16	Carrier frequency	2.0 to 12.0 kHz	Model dependent	<input type="radio"/>
P03.00	Motor type selection	0: Asynchronous motor 1: Synchronous motor	0	<input checked="" type="checkbox"/>
P03.01	Asynchronous motor rated power	0.1 to 3000.0 kW	Model dependent	<input checked="" type="checkbox"/>
P03.02	Asynchronous motor rated voltage	0 to 1200 V	Model dependent	<input checked="" type="checkbox"/>
P03.03	Asynchronous motor rated current	0.8 to 6000.0 A	Model dependent	<input checked="" type="checkbox"/>
P03.04	Asynchronous motor rated frequency	0.01 Hz to P02.10	50.00 Hz	<input checked="" type="checkbox"/>
P03.05	Asynchronous motor rated speed	1 to 36000 rpm	Model dependent	<input checked="" type="checkbox"/>
P03.15	Synchronous motor rated power	0.1 to 3000.0 kW	Model dependent	<input checked="" type="checkbox"/>
P03.16	Synchronous motor rated voltage	0 to 1200 V	Model dependent	<input type="checkbox"/>